Nationaal Lucht- en Ruimtevaartlaboratorium

National Aerospace Laboratory NLR





















AMS Tracker Thermal Control Subsystem **TTCB EMC/EMI operation procedure**

AMSTR-NLR-PR-029 ISSUE 1.0 MAY 2009

Sun Yat-Sen University (SYSU) National Aerospace Laboratory (NLR) Instituto Nazionale di Fisica Nucelare (INFN)

	NAME	ORGANISATION/RESPONSIBILITY	SIGNATURE	DATE
PREPARED	A. Pauw	NLR		
CHECKED	J. van Es	NLR / AMS TTCS System Eng.		
AGREED	PA person XYZ	NLR / AMS Company PA		
APPROVED	J. van Es	NLR / AMS TTCS PM		
AUTHORISED				

FILENAME	AMSTR-NLR-PR-XXX_TTCB_EMC_EMI_procedure2.doc	ORDER-/CODENUMBER:	
LAST SAVED	2009.06.09 07:20 by pauw	DIVISION:	
PRINTED	2009.06.09 07:26	DISTRIBUTION:	Unlimited
PAGES	15	CLASSIFICATION TITLE:	Unclassified

No part of this document may be reproduced and/or disclosed, in any form or by any means, without the prior written permission of NLR.















Page Doc.ld Issue

2 of 18 AMSTR-NLR-PR-029 1.0 (iss)

Date May 2009

TTCB EMC/EMI operation procedure

Distribution list

Company	FOR*	Name	Comments
INFN	I	R. Battiston	
		M. Menichelli	
		C. Gargiulo	
		B. Alpat	
		A. Alvino	
		E. Laudi	
AMS	ı	M. Capell	
		V. Koutsenko	
		R. Becker	
NLR	ı	P. Dieleman	
		J.van Es	
		M. Bardet	
Jacobs Sverdrup	I	T. Martin	
		G. Clark	
AIDC	I	K.M. Sun/	
		B. Hsu	
		W. Min Hsu	
CGS	ı	M. Molina	
		C. Vettore	

A = Approval R = Review

I = Input / Information

An electronic version of this document is available on the AMS TTCS website: https://ams-ttcs.nlr.nl













Page Doc.ld Issue

3 of 18 AMSTR-NLR-PR-029

> 1.0 (iss) May 2009

TTCB EMC/EMI operation procedure

Date

Document change log

Change Ref. Section(s) All

Issue 1.0

Initial issue













TTCB EMC/EMI operation procedure

Page Doc.Id Issue

4 of 18 AMSTR-NLR-PR-029

1.0 (iss) May 2009 Date

Contents

Do	ocument c	hange log	3
1	Scope of	f the document and test objective	5
2	Hardwa	are under test	5
3	Test Rec	quirements	5
4	Test faci	ility/equipment description	5
5	TTCB E	EMC/EMI Test in main steps	8
6	Referen	ces documents	8
7	TTCB E	EMC/EMI operation procedure	9
	7.1	The TTCB EMC/EMI operation procedure	9
	7.2	TTCB EMC/EMI preparation sheet	10
	7.3	TTCB EMC/EMI operation procedure sheets	12
ΕN	ND OF DO	DCUMENT	15

(15 pages in total)















Page Doc.ld Issue

5 of 18 AMSTR-NLR-PR-029 1.0 (iss)

Date

May 2009





TTCB EMC/EMI operation procedure

Scope of the document and test objective

During EMC/EMI test components of the TTCB need to operational. This document contains operation procedure sheets for the TTCB during EMC and EMC and does not include the EMC/EMI test procedure.

Hardware under test

The hardware the TTCB-p or TTCB-s are the flight modules. The TTCB shall be operational during EMC/EMI test and therefore will be connected to Ground Support Equipment to form a closed loop filled with CO2. The GSE-loop will be equipped with a mass flow meter, absolute pressure transducer, differential pressure transducer and temperature sensors.

Test Requirements 3

During the emissivity test the following actuator will be switched on to measure the emission. If possible the actuators will be switched on separately, no other actuators active or as less as possible.

	Actuator	Pump running	comment
1	Peltier elements	no	PWM, TBD %
2	Accumulator heater FAC	no	PWM, , TBD %
3	TTCB pump	yes	3500, 6000, 10000 RPM
4	Pre-heater	yes (minimal flow)	Auto control
5	Start Up Heater	yes (minimal flow)	Manual ON/OFF (2s/10s)
6	Cold Orbit Heater	yes (minimal flow)	Manual ON/OFF (2s/10s)

Test facility/equipment description

The test is performed at SERMS (Terni) at the EMC/EMI test facility and the following type of equipment will be used for operating the TTCB:

- TTCE / cables / CAN-if / pc with TTCE sw
- Mass flow meter
- Absolute transducer

No part of this document may be reproduced and/or disclosed, in any form or by any means, without the prior written permission of NLR.





Page Doc.ld Issue

6 of 18 AMSTR-NLR-PR-029 1.0 (iss)

Date

May 2009

- TTCB EMC/EMI operation procedure
- Differential pressure transducer
- Temperature sensors, TC type T
- NI cDAQ system
- Pc with LV sw
- Thermostat bath for cooling CO2 (GSE-loop)




Figure 4-1: TTCB schematic with additional tubing for functional test

No part of this document may be reproduced and/or disclosed, in any form or by any means, without the prior written permission of NLR.





Page Doc.ld Issue 7 of 18

AMSTR-NLR-PR-029

1.0 (iss)

Issue Date

May 2009

TTCB EMC/EMI operation procedure




Figure 4-2: schematic with GSE for operating TTCB















Page Doc.Id

8 of 18 AMSTR-NLR-PR-029

Issue Date

1.0 (iss) May 2009

TTCB EMC/EMI operation procedure

TTCB EMC/EMI Test in main steps

The main test steps are:

- 1. Fill the system with CO2, TTCB inside climate chamber and GSE outside climate chamber
- 2. Separate TTCB and GSE-loop for transport to EMC facility and connect the TTCB and GSE-loop in EMC facility.
- 3. Connect TTCB to TCCE
- 4. Operate TTCB and conduct EMC/EMI test
- 5. Empty TTCB
- 6. Dis-connect TTCB from TCCE

References documents

	Title	Number	Date
RD-1	TTCS Requirements	AMSTR-NLR-PL-02 Issue 1.0	April 2007
	Verification Matrix FM H/W		
	Filling procedure		

No part of this document may be reproduced and/or disclosed, in any form or by any means, without the prior written permission of NLR.













Page Doc.Id Issue

Date

9 of 18 AMSTR-NLR-PR-029 1.0 (iss)

May 2009

TTCB EMC/EMI operation procedure

TTCB EMC/EMI operation procedure

7.1 The TTCB EMC/EMI operation procedure

The TTCB EMC/EMI operation procedure sheets shall be filled in, and shall accompany the TTCB during it's lifetime in order to be able to show the procedure was followed.

During the EMC/EMI test the environment can not be cooled. Therefore it might be necessary to pause in between the EMC/EMI test steps to condition the environment or cool down the TTCB itself for safe operation of the TTCB actuators. The procedure has been written assuming an environment temperature of 20 °C or lower and humidity as low as possible.

















TTCB EMC/EMI operation procedure

10 of 18 Page

Doc.ld. AMSTR-NLR-PR-029

1.0 (iss) Issue

Date May 2009

7.2 TTCB EMC/EMI preparation sheet

	TTCB EMC/EMI preparation procedure sheets		company:		date:	
	Fill in by hand.		engineer:		location:	
Step	Action	Monitoring	Value	Result	Comment	$\sqrt{}$
1.	Record model type		P/S/QM			
2.	Cool down EMC chamber, Tenvironment	Tenvironment	T ≤ 20°C			
3.	Place TTCB in climate chamber and GSE outside climate chamber					
4.	Wrap TTCB completely in plastic foil, as leak tight as possible					
5.	Flush TTCB envelop with gN2, to remove moisture					
6.	Fill system with CO2 with DPS bypass valve open	Fill rate	TBD g/liter			
7.	Close TTCB connection valves and disconnect GSE					
8.	Verify EMC chamber temperature	Tenvironment	T ≤ 20°C			
9.	Transport to EMC/EMI test facility					
10.	Place TTCB in EMC chamber, GSE outside chamber and connect					
	tubing and TTCE.					
11.	Put thermal insulation around connection tubes					
12.	Vacuum GSE using dry scroll pump	time	5 min			

















TTCB EMC/EMI operation procedure

Page

11 of 18

Doc.ld.

AMSTR-NLR-PR-029

Issue Date

1.0 (iss) May 2009

	TTCB EMC/EMI preparation procedure sheets		company:		date:	
	Fill in by hand.		engineer:	_	location:	
Step	Action	Monitoring	Value	Result	Comment	
13.	Purge GSE-loop with CO2. Open a TCB connection valves slowly	pressure	P > 5 bar			
14.	for a few seconds.					+
14.	Vacuum GSE using dry scroll pump	time	5 min			
15.	Open both TTCB connection valves slowly.					
16.	Close DPS bypass valve					
17.	Switch on thermostat bath and set Tsetpoint	Tther.bath	T= 10 °C			
18.	End of sheet					
19.						
20.						
21.						
22.						















TTCB EMC/EMI operation procedure

Page

AMSTR-NLR-PR-029

Doc.ld. Issue

1.0 (iss)

12 of 18

Date May 2009

7.3 TTCB EMC/EMI operation procedure sheets

	TTCB EMC/EMI operation procedure sheets		company:		date:	
	Fill in by hand.		engineer:		location:	
Step	Action	Monitoring	Value	Result	Comment	
1.	Record model TTCB	model	P			
2.	Verify TTCB Tenvironment	Tenvironment	T ≤ 20°C			
	Peltier test					
3.	Switch on thermostat bath, set Tsetpoint	T cooling liquid	Tbath = $5 ^{\circ}$ C			
4.	Set / control Taccu to 23 °C	Pt01	Pt01 = 23 °C			
5.	Switch on TTCB pump for 10 min. for cooling down TTCB tubes	RPM, massflow	5000, ~ 2.2 g/s			
6.	Switch off accu heaters					
7.	Execute "EMC accu peltier test", monitor Tcopper saddle &	DS07	DS07 < 25°C			
	system pressure. (switch on peltier TBD %)	DS08	DS08 < 25°C			
		pressure	P < 65 bar			
8.	If Tcopper saddle or pressure too high then stop "EMC accu peltier test" and repeat step 4 – 6 for cooling down TTCB hw and / or cool down EMC test chamber and continue test					
	Heat pipe heater test (FAC)					

















TTCB EMC/EMI operation procedure

Page

13 of 18

Doc.ld.

1.0 (iss)

AMSTR-NLR-PR-029

Issue Date

	TTCB EMC/EMI operation procedure sheets		company:		date:	
	Fill in by hand.		engineer:		location:	
Step	Action	Monitoring	Value	Result	Comment	1
9.	Set accumulator set point, automatic control	Taccu	T=Tenv + 2 °C			
10.	Switch on TTCB pump for cooling down TTCB hw	RMP , Tloop	5000 RPM Tloop stable			
11.	Set accumulator set point, automatic control	Taccu	T=Tenv - 2 °C			
12.	Wait until Tacc = Tsetpoint	RMP, Pt01, Tloop	5000 RPM Pt01=Tsetpoint Tloop stable			
13.	Switch off pump	RPM	0			
14.	Execute "EMC accu FAC test", monitor Taccu & system pressure. (switch on FAC TBD %)	Pt01 pressure	Pt01< 25°C P < 65 bar			
15.	If Pt01 or pressure too high then stop "EMC accu FAC test", cool down EMC test chamber, repeat step 9 – 13 for cooling down TTCB hw and continue test	Tenv	Tenv ≤ 20°C			
	Pump test					
16.	Set accumulator set point, automatic control	Taccu	T=Tenv °C			
17.	Switch on TTCB pump for cooling down TTCB hw	RMP , Tloop	5000 RPM Tloop stable			















TTCB EMC/EMI operation procedure

Page

14 of 18

AMSTR-NLR-PR-029

Doc.ld. Issue

1.0 (iss)

Date

	TTCB EMC/EMI operation procedure sheets		company:		date:	
	Fill in by hand.		engineer:		location:	
Step	Action	Monitoring	Value	Result	Comment	
18.	Wait until Tacc = Tsetpoint	RMP,	5000 RPM			
		Pt01	Pt01=Tsetpoint			
19.	Set pump to 3500 RPM	Pump RPM	3500			
20.	Execute "EMC pump test", monitor Taccu , system pressure,	Taccu	Taccu < 25 °C			
	Tpmp_inlet	Psystem	P < 65 bar			
		Pt02	Pt02 <taccu 3<="" td="" –=""><td></td><td></td><td></td></taccu>			
21.	If Pt01 or pressure too high then stop "EMC pump test", cool down	Tenv	Tenv ≤ 20°C			
	EMC test chamber, repeat step 16-18 for cooling down TTCB hw					
	and continue test					
22.	Set pump to 6000 RPM	Pump RPM	6000 RPM			
23.	Execute "EMC pump test", monitor Taccu , system pressure,	Taccu	Taccu < 25 °C			
	Tpmp_inlet	Psystem	P < 65 bar			
		Pt02	Pt02 <taccu 3<="" td="" –=""><td></td><td></td><td></td></taccu>			
24.	If Pt01 or pressure too high then stop "EMC pump test", cool down	Tenv	Tenv ≤ 20°C			
	EMC test chamber, repeat step 16-18 for cooling down TTCB hw					
	and continue test					
25.	Set pump to 10000 RPM	Pump RPM	10000 RPM			















TTCB EMC/EMI operation procedure

Page AMSTR-NLR-PR-029

15 of 18

Doc.ld. Issue

1.0 (iss)

Date

	TTCB EMC/EMI operation procedure sheets		company:		date:	
	Fill in by hand.		engineer:		location:	
Step	Action	Monitoring	Value	Result	Comment	
26.	Execute "EMC pump test", monitor Taccu , system pressure,	Taccu	Taccu < 25 °C			
	Tpmp_inlet	Psystem	P < 65 bar			
		Pt02	Pt02 <taccu 3<="" td="" –=""><td></td><td></td><td></td></taccu>			
27.	If Pt01 or pressure too high then stop "EMC pump test", cool down	Tenv	Tenv ≤ 20°C			
	EMC test chamber, repeat step 16-18 for cooling down TTCB hw and continue test					
	Pre-heater test					
28.	Set accumulator set point, automatic control	Taccu	T=Tenv + 2 °C			
29.	Switch on TTCB pump for cooling down TTCB hw until TTCB is	RMP, Tloop	5000 RPM			
	cooled down		Tloop stable			
30.	Swich off accu control (heater & peltier), set pump RPM to minimal	Accu controll	OFF			
	flow, switch on pre-heater automatic control	Pump RPM	2500			
		Pre-htr control	ON			
31.	Execute "EMC pre-heater test", monitor Taccu, system pressure,	Taccu	Taccu < 25 °C			
	Tpmp_inlet	Psystem	P < 65 bar			
		Pt02	Pt02 <taccu 3<="" td="" –=""><td></td><td></td><td></td></taccu>			
32.	If Pt01 or pressure too high then stop "EMC pre-heater test", cool	Tenv	Tenv ≤ 20°C			

















Page

16 of 18

Doc.ld.

AMSTR-NLR-PR-029 1.0 (iss)

Issue Date

	TTCB EMC/EMI operation procedure sheets		company:		date:	
	Fill in by hand.		engineer:		location:	
Step	Action	Monitoring	Value	Result	Comment	
	down EMC test chamber, repeat step 28-29 for cooling down TTCB hw and continue test					
	Start up heater test (SUP)					
33.	Set accumulator set point, automatic control	Taccu	T=Tenv + 2 °C			
34.	Switch on TTCB pump for cooling down TTCB hw until TTCB is cooled down	RMP , Tloop	5000 RPM Tloop stable			
35.	Swich off accu control (heater & peltier), set pump RPM to minimal flow	Accu control Pump RPM	OFF 2500			
36.	Execute "EMC start-up heater test", monitor Taccu , system pressure, Tpmp_inlet. Manual switch on / off (2s / 10s) SUP	Taccu Psystem Pt02	Taccu < 25 °C P < 65 bar Pt02 <taccu 3<="" td="" –=""><td></td><td></td><td></td></taccu>			
37.	If Pt01 or pressure too high then stop "EMC start-up heater test", cool down EMC test chamber, repeat step 33-34 for cooling down TTCB hw and continue test	Tenv	Tenv ≤ 20°C			
	Cold orbit heater test					
38.	Set accumulator set point, automatic control	Taccu	T=Tenv + 2 °C			















TTCB EMC/EMI operation procedure

Page

17 of 18

Doc.ld.

AMSTR-NLR-PR-029 1.0 (iss)

Issue Date

	TTCB EMC/EMI operation procedure sheets		company:		date:	
	Fill in by hand.		engineer:		location:	
Step	Action	Monitoring	Value	Result	Comment	$\sqrt{}$
39.	Switch on TTCB pump for cooling down TTCB hw until TTCB is	RMP, Tloop	5000 RPM			
	cooled down		Tloop stable			
40.	Swich off accu control (heater & peltier), set pump RPM to minimal	Accu control	OFF			
	flow	Pump RPM	2500			
41.	Execute "EMC COH test", monitor Taccu , system pressure,	Taccu	Taccu < 25 °C			
	Tpmp_inlet. Manual switch on / off (2s / 10s) COH	Psystem	P < 65 bar			
		Pt02	Pt02 <taccu -="" 3<="" td=""><td></td><td></td><td></td></taccu>			
42.	If Pt01 or pressure too high then stop "EMC COH test", cool down	Tenv	Tenv ≤ 20°C			
	EMC test chamber, repeat step 38 - 40 for cooling down TTCB hw					
	and continue test					
43.						

















Page Doc.Id Issue

Date

18 of 18 AMSTR-NLR-PR-029

1.0 (iss)

May 2009

TTCB EMC/EMI operation procedure

END OF DOCUMENT